

Dc Gear Motor

Typical Application:

Electric toy, Projector, Robot, Beauty apparatus, Door lock



Model	Voltage	No Load		Load		
	Normal	Speed	Current	Torque		Current
		r/min	mA	kg/cm	n.m	mA
JL-16A050	12	250	5	0.7	0.07	600

Number Of Stages	3	4	5	6	7
Gear Ratio I	11.1	22.2	83.3	200	600
	16.7	33.3	100	250	750
		50	150	300	900
				450	1350
Length Of Gearbox L (mm)	12.8	12.8	14.2	15.6	17.9

Mechanical Dimensions

